

Channel Priority Key

When using the Retevis Ailunce HAIG GMRS radios, the standard configuration is to have your ZONE channel displayed on the top part of the display (Band A) and the AIEOC channel displayed on the bottom part of the screen (Band B). This enables the user to monitor both channels and is useful particularly when listening. But in the event the user is active on one band and there is traffic on the other band, this can become confusing. One band will interrupt the other band making copy difficult. If the user does not want to be interrupted and give priority to either Band A (top) or Band B (bottom) , there is a single key press that can accomplish this as follows:

Press the key in the lower right of the radio keypad (Labeled “#Lock”). The display will change to only show the current highlighted channel. This will be the only channel you can hear. Click the bottom again and it will go back to the normal two channel mode.



Example Usage: You are communicating on your Zone channel and you hear a message on the AIEOC “ Prepare to copy an update message from the Anderson Island EOC”. Immediately highlight your AIEOC channel (press *Scan) and then momentarily press “#Lock Key” You will only hear the broadcast message from the AIEOC. (Note, do not “long press” this key for this function, just a quick press).